







T-8			
1	D0	2	GND
3	D1	4	GND
5	D2	6	GND
7	D3	8	GND
9	D4	10	GND
11	D5	12	GND
13	D6	14	GND
15	D7	16	GND
17	BUS φ	18	GND
19	A0	20	RESET
21	A1	22	EX RESET
23	A2	24	HALT
25	A3	26	IEOA
27	A4	28	MI
29	A5	30	EX WAIT
31	A6	32	WR
33	A7	34	GND
35	A8	36	RD
37	A9	38	GND
39	A10	40	TORQ
41	A11	42	GND
43	A12	44	MERQ
45	A13	46	GND
47	A14	48	EXINT
49	A15	50	NMI

T-12			
1	Vcc	2	Vcc
3	D2	4	D3
5	D1	6	D4
7	D0	8	D5
9	GND	10	D6
11	A15	12	D7
13	A14	14	BUS φ
15	A13	16	MI
17	A12	18	WR
19	A11	20	RD
21	A10	22	TORQ
23	A9	24	MERQ
25	A8	26	GND
27	A7	28	HALT
29	A6	30	IEI
31	A5	32	IEO
33	A4	34	RESET
35	A3	36	EX RESET
37	A2	38	INT/P
39	A1	40	EX WAIT
41	A0	42	NMI
43	GND	44	GND

T-6	
CCOLOR ENCODER	
1	GND
2	CSYNC
3	CVIDEO
4	HSYNC
5	VSNC
6	GND
7	Vcc
8	G
9	R
10	B
11	COLR
12	GND

T-7			
A		B	
1	RD1 (STB)	2	GND
3	RD1	4	GND
5	RD2	6	GND
7	RD3	8	GND
9	RD4	10	GND
11	RD5	12	GND
13	RD6	14	GND
15	RD7	16	GND
17	RD8	18	GND
19	IRT (RST)	20	GND
21	RDA (BUSY)	22	GND
23	STA	24	GND

T-9	
CASET	
1	EX WRITE
2	EX READ
3	GND
4	MOTOR
5	SENCE
6	+5V
7	WRITE
8	READ
9	GND

T-10	
JOYSTICK B	
1	Vcc
2	V BLNK
3	JB 1
4	JB 2
5	GND

T-11	
JOYSTICK A	
1	Vcc
2	V BLNK
3	JA 1
4	JA 2
5	GND

T-13	
1	L-CH
2	GND
3	R-CH
4	GND
5	GMOD
6	PRSW
7	TPSW
8	Vcc
9	GND
10	WRITE
11	READ
12	SENCE
13	MOTOR
14	GND
15	GND

T-14	
QD	
1	WRPR
2	WRDT
3	WRGA
4	MT ON
5	RDDT
6	REDY
7	MDST
8	MSTP
9	Vcc
10	GND

T-15	
VOICE	
1	VOICE
2	ACK
3	ACL
4	N I
5	O E
6	BUSY
7	DATA
8	Vcc
9	GND

DIP SW			
NO	NAME	ON	OFF
1	TP SW	NORMAL	INV
2	PR SW	MZ PRINTER	CENTER PRINTER
3	GMOD	GRAPHIC NON	GRAPHIC
4			